

# Cleaning Procedure

## Quick Cleaning Procedure for 3D Printing Area

**Total Time: 8 Minutes**

### 1. Preparation (1 Minute)

- **Gather Cleaning Supplies:** Collect all necessary cleaning tools and materials, such as isopropyl alcohol, microfiber cloths, plastic scrapers, a small broom, dustpan, and waste bins.

### 2. Clear the Build Area (2 Minutes)

- **Remove Debris:** Carefully remove any loose filament strands, failed prints, and raft materials from the build plate and surrounding area.
- **Dispose of Waste:** Immediately place all debris into the designated recycling bin or trash depending on the material type.

### 3. Clean the Build Plate (2 Minutes)

- **Wipe Down:** Spray a small amount of isopropyl alcohol on the build plate and gently wipe with a microfiber cloth to remove any adhesive residue or leftover filament.
- **Check for Stickiness:** Ensure the surface is not sticky; if residue persists, use a plastic scraper gently to remove any stubborn spots.

### 4. Sweep the Area (1 Minute)

- **Sweep Up:** Use a small broom to sweep the floor and areas around the printer, focusing on gathering any dust, filament fragments, and other small debris.
- **Collect with Dustpan:** Pick up the swept debris with a dustpan and dispose of it properly.

### 5. Inspect and Wipe Printer Exterior (1 Minute)

- **Quick Inspection:** Visually inspect the printer for any spilled materials or dust.

- **Clean Exterior:** Wipe down the exterior surfaces of the printer with a dry microfiber cloth to remove dust and potential spills.

## 6. Organize Supplies (1 Minute)

- **Return Supplies:** Put back all cleaning materials and tools to their designated storage spots.
- **Ready for Next Use:** Ensure that the printer is set up for the next user, with the build plate correctly aligned and the filament guide clear.

**By incorporating sweeping into the cleaning routine, you ensure that the area not only stays free of large debris but also maintains a level of cleanliness that prevents dust and small particles from affecting printer operation and product quality.**

---

Revision #1

Created 6 May 2024 03:51:23 by Ian G

Updated 6 May 2024 04:09:29 by Ian G